

LCDUWS

SECURITY LCD WALL MOUNT FOR 75MM x 75MM, 100MM x 100MM & 200MM X 100MM VESA PATTERNS

1. Determine location of LCD and using wall plate for a template cut access hole into drywall for running video and power cables.
2. Attach wall plate to wall using two #14 x 2.5" tapping screws into center of wood stud. Use two 1/4-20 toggle bolts into drywall (see toggle bolt instruction sheet for details). Put grommet onto lower section of wall plate as shown.
3. Place LCD on non-abrasive surface screen side down. Place two fender washers over each mounting hole. Align LCD adapter plate over washers and attach LCD adapter plate to monitor using screws appropriate to your LCD (4M x 12MM Phillips pan head screws are provided).
4. Attach LCD screen with adapter plate to wall plate by placing rivets on back of adapter plate into slots on wall plate and lowering (run all cables through back of wall plate and into monitor before securing).
5. Secure plates together using #10-24 x 1" Machine Screw (security screw is optional requires tool part #SH10ASKT) .

