

INSTRUCTIONS: Display Fixture
Model: DL-167-BK

IMPORTANT SAFETY INSTRUCTIONS Lighted lamp is **HOT**:
WARNING – To reduce the risk of FIRE, ELECTRIC SHOCK, EXPOSURE TO EXCESSIVE UV RADIATION, OR INJURY TO PERSONS:

1. Turn off/unplug and allow to cool before replacing bulb (lamp).
2. Bulb (lamp) gets **HOT** quickly! Only contact switch/plug when turning on.
3. Do not touch hot lens, or guard.
4. Do not remain in light if skin feels warm.
5. Do not look directly at lighted lamp.
6. Keep lamp away from materials that may burn.
7. Use only with a 50-watt or smaller bulb (lamp).
8. Do not touch the bulb (lamp) at any time. Use a soft cloth. Oil from skin may damage bulb (lamp).
9. Do Not operate the luminaire with a missing guard.

SAVE THESE INSTRUCTIONS

Installing Lamp:

1. Use 12V MR16-G lamps (UV protected & glass covered), 50 watt maximum (purchase separately).
2. Align lamp pins with socket holes and gently press in.
3. Using a fine blade screwdriver, tighten the lamp-retaining screws on the bottom of the socket.
4. Note: remember to loosen these screws when re-lamping.

Installing Clamp:

1. Installs on a firm flat surface, such as wood, particleboard, cubicle partition etc. Standard clamp accommodates surfaces up to 2" thick.
2. Use the angle adjustment knob on the side to change the angle.
3. Adjust the height by sliding the telescoping rods. Socket will be hot, grasp by the rods.

Accessories:

1. Supplied with standard clamp that opens to 2" wide.
2. An optional "DLC-4A-BK" clamp opens to 4".
3. Standard clamp may also be used on 2" diameter pipe.
4. Open MR16 lamps may be used in conjunction with the "LENS-CLIP" and various accessory lenses.

