



Catalog Information

Model	Description	Lamp/Max Watt	Voltage	CH	PT	SB
WS-MR52	Metal round style	JC-50/50W*	120V to 12V			

*Included with Socket Set
 Finish Key: CH = Chrome, PT= Platinum, SB-Satin Brass

Product Features

- Description:** Low voltage wall sconce. With round metal front fascia. Includes a self-contained electronic transformer. Fits selected WAC G500 series glass shades.
- Lamp:** Uses a 12 volt, 50 watt bi pin-Halogen lamp with G6.35 base (supplied). Retained by a screw on frosted bulb shield
 - Transformer:** Electronic 60 watt transformer. Built in auto reset short and overload protection. "Soft start" delayed start extends lamp life.
 - Dimming:** Dimmable with electronic dimmer or generally dimmable with a standard incandescent dimmer (High Frequency output is compatible with most standard dimmers).
 - Mounting:** Installs to a standard 4" junction box. The screw on bulb shield retains the glass shade.

Shades

- G511 Cased glass : AM, BL, RD, WT, YW
- G512 Cased glass : AM, BL, RD, WT, YW
- G515 Multi color glass : BW, MF, RW
- G516 Multi color glass : BL, PR
- G518 Pressed glass : DIC (dichroic coating)

Color Key :

AM=Amber, BL=Blue, RD=Red, WT=White, RD=Red
 BW=Blue/White, MF=Milefiore, RW=Red/White, PR=Purple.

Material

Brass, with plated or painted finish, ceramic bi pin socket.

Listings

UL, CUL Listed.

W.A.C. reserves the right to change details that do not affect overall function and performance.

