



Catalog Information

Model	Description	Lamp/Max Watt	Voltage	Finishes		
WS-MR54	Metal round style	JC-50/50W*	120V to 12V	CH	PT	SB

*Included with Socket Set
 Finish Key: CH = Chrome, PT= Platinum, SB-Satin Brass

Product Features

- Description:** Low voltage wall sconce. With round metal front fascia. Includes a self-contained electronic transformer. Fits only the WAC G513 series glass shade.
- Lamp:** Uses a 12 volt, 50 watt bi pin-Halogen lamp with G6.35 base (supplied). Retained by a screw on frosted bulb shield
 - Transformer:** Electronic 60 watt transformer. Built in auto reset short and overload protection. "Soft start" delayed start extends lamp life.
 - Dimming:** Dimmable with electronic dimmer or generally dimmable with a standard incandescent dimmer (High Frequency output is compatible with most standard dimmers).
 - Mounting:** Installs to a standard 4" junction box. Shade is held by wire springs and spring tabs.

Shades

G513 Cased glass : AM, BL, WT,
 Color Key :
 AM=Amber, BL=Blue, WT=White,

Material

Brass, with plated or painted finish, ceramic bi pin socket.

Listings

UL, CUL Listed.

W.A.C. reserves the right to change details that do not affect overall function and performance.

