



**Catalog Information**

Model	Description	Lamp/Max Watt	Voltage	CH	PT	SB
WS-MS54	Metal square style	JC-50/50W*	120V to 12V			

\*Included with Socket Set  
 Finish Key: CH = Chrome, PT= Platinum, SB-Satin Brass

**Product Features**

- Description:** Low voltage wall sconce. With square metal front fascia. Includes a self-contained electronic transformer. Fits only the WAC G513 series glass shade.
- Lamp:** Uses a 12 volt, 50 watt bi pin-Halogen lamp with G6.35 base (supplied). Retained by a screw on frosted bulb shield
  - Transformer:** Electronic 60 watt transformer. Built in auto reset short and overload protection. "Soft start" delayed start extends lamp life.
  - Dimming:** Dimmable with electronic dimmer or generally dimmable with a standard incandescent dimmer (High Frequency output is compatible with most standard dimmers).
  - Mounting:** Installs to a standard 4" junction box. Shade is held by wire springs and spring tabs.

**Shades**

G513 Cased glass : AM, BL, WT,  
 Color Key :  
 AM=Amber, BL=Blue, WT=White,

**Material**

Brass, with plated or painted finish, ceramic bi pin socket.

**Listings**

UL, CUL Listed.

W.A.C. reserves the right to change details that do not affect overall function and performance.

