



Catalog Information

Model	Description	Lamp/Max Watt	Voltage	CH	PT	SB
WS-MS61	Metal square style	JC-50/50W*	120V to 12V			

*Included with Socket Set
 Finish Key: CH = Chrome, PT= Platinum, SB-Satin Brass

Product Features

- Description:** Low voltage wall sconce. With square metal front fascia. Includes a self-contained electronic transformer. Fits all WAC G600 series glass shades.
- Lamp:** Uses a 12 volt, 50 watt bi pin-Halogen lamp with G6.35 base (supplied). Retained by a screw on frosted bulb shield
 - Transformer:** Electronic 60 watt transformer. Built in auto reset short and overload protection. "Soft start" delayed start extends lamp life.
 - Dimming:** Dimmable with electronic dimmer or generally dimmable with a standard incandescent dimmer (High Frequency output is compatible with most standard dimmers).
 - Mounting:** Installs to a standard 4" junction box. The shade is retained by the socket assembly. Socket attaches to fixture by means of a quick connect jack.

Shades

- G613 Cased glass : AM, BL, GR, RD, WT, YW
- G611 Cased glass : AM, BL, GR, RD, WT, YW
- G612 Fluted cased : BL, WT
- G615 Multi color glass : BG, RP, YP
- G614 Multi color glass : BG, MF, YR,

Color Key :
 AM=Amber, BL=Blue, RD=Red, WT=White, YW=Yellow
 BG=Blue/Green, RP=Red/Purple, RW=Red/White,
 YP=Yellow/Purple, MF=Milifiore, YR=Yellow/Red.

Material

Brass, with plated or painted finish, ceramic bi pin socket.

Listings

UL, CUL Listed.

W.A.C. reserves the right to change details that do not affect overall function and performance.

